






## Sockets



For all nozzles with	Ordering no.				G BSPP	Dimensions [mm]				Weight [g] (Brass)	
	Type	Mat. no.				H <sub>1</sub>	H <sub>2</sub>	Ø D	Hex		
		1Y	17	30							53
1/8" male thread	040.270	●		●		1/8	20.0	10.0	13.8	14	20.0
1/4" male thread	061.220	●		●		1/4	20.0	10.0	16.8	17	20.0
3/8" male thread	040.271	●		●		3/8	20.0	10.0	21.8	22	25.0
	040.271				●	3/8	20.0	11.0	25.0	22	25.0
1/2" male thread	040.272		●	●		1/2	30.0	15.0	26.5	27	70.0
3/4" male thread	061.620		●	●		3/4	40.0	20.0	31.5	32	108.0

**Notice:** Sockets are also suitable for welding.

## Sockets with radius




For all nozzles with	Ordering no.		G BSPP	Dimensions [mm]			Weight [g]
	Type	Mat. no.		H <sub>1</sub>	H <sub>2</sub>	Ø D	
		1Y					
1/4" male thread	040.228.1Y.yy <sup>1</sup>	●	1/4	18.0	12.0	17.0	16.0

<sup>1</sup> Replace "yy" with the desired radius R (R = 10/13/16/20/25 or 31 mm).

Ordering Type + Material no. = Ordering no.  
example: 040.270 + 1Y = 040.270.1Y




## Sockets



Connection components	Ordering no.			G <sub>1</sub> BSPP	G <sub>2</sub> BSPP	Dimensions [mm]			Weight [g] (Brass)
	Type	Mat. no.				L <sub>1</sub>	L <sub>2</sub>	Hex	
		17	30						
		Stainless steel 316Ti	Brass						
1/8" to 3/8"	<b>040.211</b>	●	●	1/8	3/8	20.0	10.0	22	40.0
1/4" to 3/8" short	<b>065.221</b>	●	●	1/4	3/8	23.0	10.0	22	40.0
1/4" to 3/8" long	<b>065.228</b>	●	●	1/4	3/8	36.0 <sup>1</sup>	14.0	19	45.0
3/8" to 3/8"	<b>065.220</b>	●	●	3/8	3/8	25.0	10.0	22	40.0
3/4" to 3/4"	<b>065.620</b>	●	●	3/4	3/4	35.0	14.0	32	280.0

<sup>1</sup> Mounting of nozzle filters and ball-type non-return valves possible (see Page 284/285).

## Reduction socket



Connection components	Ordering no.			G <sub>1</sub> BSPP	G <sub>2</sub> BSPP	Dimensions [mm]			Weight [g]
	Type	Mat. no.				L <sub>1</sub>	L <sub>2</sub>	Hex	
		1Y	30						
		Stainless steel 316L	Brass						
3/8" to 1/4"	<b>095.019.30.00.23</b>		●	3/8	1/4	26.0	12.0	22	55.0

Ordering Type + Material no. = Ordering no.  
example: 040.211 + 17 = 040.211.17